

Sound Master

www.soundmaster-es.com

TS-1000

TS-1000

Dual Channel
Wireless Microphone



LAVALIER



HEADSET

Specifications :

- Frequency Range: 635~675MHz .
- Frequency Quantity: 200 frequencies
- Signal-to-Noise Ratio: 105dB .
- Total Harmonic Distortion: <0.5% .
- Modulation Mode: Analog.
- Frequency Response: 60HZ~18KHZ(± 2 dB) Working.
- Distance: 450~800 meters
- Channel Interval: 300KHz
- Sensitivity : -95 dB .

Receiver Parameter:

- Oscillation Mode: PLL Sensitivity: 12dBuV(80dB S/N)
- Power Supply Mode: DC12V,1000mA

Transmitter Parameter:

- Output Power: 10mW~15mW Directivity: Cardioid pickup pattern
- Frequency Response 635~675MHz .

Dual Channel Wireless Microphone (Lavalier/ head seat ,headphone and handheld)